



CO-TX-MNL3

| Transmitter CO-TX-MNL3 | |
|-------------------------------|--|
| Article no. | T60-T8-52 |
| Frequency | 433 MHz , 1 channels |
| Mod.type | FM-modulation |
| Code comb. | 16.777.216 |
| Radio type | Fractional-N PLL |
| Output | 10 mW (by 50 ohm) |
| Buttons | 3 x 1 -step buttons |
| No. of batteries | 2 |
| Battery | Exchangeable |
| Type of batteries | 1.5V AAA |
| Weight | ~ 80 g / ~ 0.2 lb |
| Dimensions | ~ 52 x 83 x 17 mm / ~ 2 x 3.3 x 0.7 in |
| Protection | IP67 |
| Temperature | -20 to +55 C / -4 to +130 F |
| On/off switch | Yes |
| Features/miscellaneous | On/off switch |

The product picture above is for illustrative purposes only, actual product appearance might be slightly different.