

LION



LI-TX-JD02

| Transmitter LI-TX-JD02                      |   |
|---|---|
| <b>Article no.</b>                          | 860JD-T4-3  |
| <b>Frequency</b>                            | 433 MHz , 69 channels                             |
| <b>Mod.type</b>                             | FM-Modulation, narrow band                        |
| <b>Code comb.</b>                           | 65.536  |
| <b>Radio type</b>                           | Low IF topology                                   |
| <b>Output</b>                               | 10 mW (by 50 ohm)                                 |
| <b>Buttons</b>                              | 4 x 1 -step buttons                               |
| <b>No. of batteries</b>                     | 1   |
| <b>Battery</b>                              | Re-chargeable & exchangeable                      |
| <b>Type of batteries</b>                    | li-ion  |
| <b>Operating time with continuous usage</b> | 15 h  |
| <b>Weight</b>                               | ~ 1200 g / ~ 2.6 lb                               |
| <b>Dimensions</b>                           | ~ 210 x 140 x 130 mm / ~ 8.3 x 5.5 x 5.1 in       |
| <b>Protection</b>                           | IP65  |
| <b>Temperature</b>                          | -20 to +55 C / -4 to +130 F                       |
| <b>Safety level</b>                         | CAT3, PLd   |
| <b>On/off switch</b>                        | Yes   |
| <b>Joysticks</b>                            | 2 joysticks with 2 speeds (left= x + y, right= y) |

The product picture above is for illustrative purposes only, actual product appearance might be slightly different.