



CO-TX-MNL1

Transmitter CO-TX-MNL1	
<b>Article no.</b>	T60-T8-53
<b>Frequency</b>	433 MHz , 1 channels
<b>Mod.type</b>	FM-modulation
<b>Code comb.</b>	16.777.216
<b>Radio type</b>	Fractional-N PLL
<b>Output</b>	10 mW (by 50 ohm)
<b>Buttons</b>	1 x 1 -step buttons
<b>No. of batteries</b>	2
<b>Battery</b>	Exchangeable
<b>Type of batteries</b>	1.5V AAA
<b>Weight</b>	~ 80 g / ~ 0.2 lb
<b>Dimensions</b>	~ 52 x 83 x 17 mm / ~ 2 x 3.3 x 0.7 in
<b>Protection</b>	IP67
<b>Temperature</b>	-20 to +55 C / -4 to +130 F
<b>On/off switch</b>	Yes
<b>Features/miscellaneous</b>	On/off switch

The product picture above is for illustrative purposes only, actual product appearance might be slightly different.